

1650 McReynolds Avenue, N.W.
 Grand Rapids, Michigan 49504-2043
 Phone: (616) 363-4416 Fax: (616) 363-0380
 www.bulmanproducts.com

WORK TABLES WITHOUT SHELVING (A80-36/A80-06)

1. Table unit is shipped complete in one carton containing legs, braces, and all hardware for assembly.
2. To begin assembly, place table top upside down on flat surface. Attach right and left leg assemblies to the pre-attached channels as shown in Figure 1. (View A) (Do not fully tighten 1/4" hex bolt and nut.)
3. Attach rear brace as shown in Figure 1. All leg and brace connections may now be securely tightened.
4. Table may now be turned over into upright position. Adjust leveling screw on bottom of each leg to secure unit in place.
5. If unit is provided with accessories drawer, simply slide into pre-attached drawer channels as shown in Figure 1.

Hardware

<u>Quantity</u>	<u>Description</u>	<u>Part No.</u>
12	1/4 -20 x 2" Hex Head Grade 5 Bolts	67070
4	3/4" – 10 x 3" Carriage Bolts	67015
4	3/4" – 20 Jam Nuts	67016
12	1/4" Flat Washers	1040
12	1/4" – 20 Keps Hex Nuts*	11860

*The Keps nuts are hex nuts with a free spinning lock washer attached.



A80-36 Table shown above.



A80-06 Table shown above.

A670 FULL FUNCTION TABLE, A80-35, 6 STANDARD PACKING TABLE, A80-05, 6 BASIC PACKING TABLE

FIGURE 1

VIEW A

